

# D-OX

## TECHNICAL DATA SHEET | 7174


### D-OX Dissolves Corrosion, Carbon & Oxide Deposits

- Oil-based contact cleaner with European-style formulation
- Dissolves oxide, sulphide and carbon deposits
- Cleans and lubricates metallic contact surfaces
- Leaves light protective film preventing future corrosion
- Safe for PCBs, use only on de-energised circuits



Safety Data Sheet

#### Dual Action Spray



**Chemz D-Ox** is an oil-based cleaner designed to restore, clean, and protect electrical contacts and metallic surfaces. It effectively removes carbon, sulphide and oxide layers from switches, sliding contacts, contact banks, relays, PC boards, telecommunications, data processing equipment and multi-plugs, including after carbon flashover contamination. Specially formulated inhibitors provide long-term lubrication and corrosion protection while leaving a light protective film to prevent future corrosion. Ideal for auto electrical and marine applications, Chemz D-Ox ensures reliable performance and extended service life when used on de-energised circuits.



### CHEMZ D-OX

**CODE:** 7174

**SIZE:** 400ml

**PROPELLANT:** Hydrocarbon

**BASE:** Oil

MPI APPROVED C12 (All animal products except dairy)

#### APPLICATIONS:

**PRECAUTIONS:** Read label before use. Keep out of reach of children. Wash hands thoroughly after handling. Gloves and eye protection are recommended in an industrial environment. Avoid breathing vapours/spray. Use only in a well-ventilated area. In confined areas, use a respirator. Do not eat, drink or smoke when using this product.

**INDUSTRIAL & MANUFACTURING** - Cleans and protects switches, relays and contact banks

**TRANSPORT & LOGISTICS** - Maintains connectors, PCBs, multi-plug systems

**CONSTRUCTION & MINING** - Protects control panels and metallic contacts

**RURAL & AGRICULTURAL** - Cleans machinery electrical contacts and switches

**MARINE & FISHING** - Protects relays and sensitive electronics

**DIRECTIONS:** De-energise equipment before use. Spray Chemz D-OX onto metal surfaces, ensuring complete wetting. For heavy contamination, gently brush into the surface. Remove loosened contaminants with Chemz Contact Cleaner (#7174) before re-energising equipment.

Appearance	Clear red liquid spray
Vapour Density, (Air = 1)	>1
Flashpoint, °C	<0 (Hydrocarbon propellant)
Propellant	Hydrocarbon

#### MANUFACTURED BY:

CHEMZ Limited, 80 Rangitane Road  
Whakatu, Hastings, 4180 New Zealand  
Phone: 06 877 9690

#### EMERGENCY CALL:

**0800 764 766**  
**NZ POISON CENTRE (24HR)**



[www.chemz.co.nz](http://www.chemz.co.nz)

